

- C** Select your country and ISP (set to Streamyx), then complete the **Internet Settings** with the information provided by your ISP: Connection Type (set to PPPoE/PPPoA), Streamyx Username and Password, VPI (set to 0), and VCI (set to 35). Click **NEXT** to continue.

Quick Start - Internet Settings

Country:

ISP:

ISP Connection Type:

Username:

Password:

VPI: (0~255)

VCI: (32~65535)

Connection Type:

Enter Streamyx username and password.

Note: Please make sure to enter @streamyx in the username box as shown.

Record your Streamyx information here.

Username: _____@streamyx
Password: _____

- D** Verify or change the **Wlan** settings (wireless network settings) and click **NEXT** to continue.

Note: You may personalize your SSID (wireless network name) and pre-shared key (password). Once done, you will have to reconnect to your wireless network using the new SSID and key.

Quick Start - Wlan

Access Point: Activated Deactivated

SSID:

Broadcast SSID: Yes No

Authentication Type:

Encryption:

Pre-Shared Key:

Enter a new Wi-Fi name.

Enter a new Wi-Fi password.

Record your wireless information here.

SSID (Wireless Network Name):

Pre-Shared key (Password):

- E** Click **SAVE** to complete the configuration.

Quick Start Complete!!

The Setup Wizard has completed. Click **BACK** to modify changes or mistakes. Click **SAVE** to save the current settings.

Note: If the Access Point is activated, the wireless function will be available even without the external antenna because of an additional printed antenna.

TOLL FREE 1300 88 875 465
Service Center TP-Link (24/7)