


# Quick Installation Guide

AC750 Wireless Dual Band Router  
Archer C20



## 1. Connect the Hardware

**1** **Power off** the modem, and remove the backup battery if any.

**2** Connect the modem to the Internet port on your router with an Ethernet cable.

**3** **Power on** the modem, wait for 2 minutes and then **power on** the router.

**4** Check the following LEDs to ensure the hardware connection is correct.

Note: If your Internet comes via an Ethernet cable from the wall instead of any DSL/Cable/Satellite modems, please connect the Ethernet cable directly to the router's Internet port.

## 2. Configure the Router

**1** Connect your computer to the router (Wired or Wireless).

**• Wired**

**• Wireless**

Connect wirelessly by using the default SSID (network name) and password printed on the label at the bottom of the router.

Or

**2** Open a web browser on the computer and configure the router according to the following main clues.

**a** Enter **http://tplinkwifi.net** in the address bar. Alternatively, enter **http://192.168.0.1** or **http://192.168.1.1**.

Type in **admin** for both the user name and password and click **Login**.

Note: If the login window does not appear, please refer to FAQ->Q1.

**b** Select your WAN Connection Type, or click **Auto-Detect** if you are unsure what your connection type is. Click **Next** and follow the instructions to continue.

Note: If an Internet connection is already established, the Quick Setup wizard will bypass Step **b** and go to Step **c**.

**c** Choose the frequency(s) you prefer and then click **Next**.

**d** Verify or change the wireless network settings, and click **Next**.

Note: You may customize your 2.4GHz/5GHz wireless network name and password. Once done, the wireless connection will disconnect automatically, and you must then use the new wireless network name/password to regain access to the Internet.

**e** Click **Finish** to complete the setup.

**Enjoy!**

Now your wired and wireless devices can connect to the Internet!

# Tether App

TP-LINK's Tether App allows you manage the router on smart devices. You can:

- View the information about wireless clients.
- Parent-control your kid's access to the Internet.
- Block or Unblock wireless access to the Internet via the router.
- Configure some basic settings for the router.

Then, how to start?


- 1 Scan the QR code and download the TP-LINK Tether App from App Store or Google Play.
- 2 Ensure your smart device is wirelessly connected to the router.
- 3 Launch the Tether App, and enjoy the easy management of the router.



# USB Features

The USB port can be used for media sharing, storage sharing and print sharing across your local network. You can also set up an FTP server to access your files remotely through the Internet.

Note: To learn more about the USB features, please visit <http://tp-link.com/app/usb>, or simply scan the QR code with your smart devices.



# Frequently Asked Questions (FAQ)

## Q1. What can I do if the login window does not appear?

- A1. If the computer is set to a static or fixed IP address, change it to obtain an IP address automatically.
- A2. Verify that <http://tplinkwifi.net> is correctly entered in the web browser. Alternatively, enter <http://192.168.0.1> or <http://192.168.1.1> in the web browser and press Enter.
- A3. Use another web browser and try again.
- A4. Reboot your router and try again.
- A5. Disable the network adapter used currently and then enable it again.

## Q2. What can I do if I cannot access the Internet?


- A1. Check if the Internet is working properly by connecting a computer directly to the modem via Ethernet cable. If not, contact your Internet Service Provider.
- A2. Open a web browser, enter <http://tplinkwifi.net> and try to set up again.
- A3. Reboot your router and try again.

Note: For cable modem users, reboot the modem first. If the problem still exists, go to **Network>MAC Clone**, then click **Clone MAC Address** and **Save**.

MAC Clone	
WAN MAC Address:	<input type="text" value="xx-xx-xx-xx-xx-xx"/> <input type="button" value="Restore Factory MAC"/>
Your PC's MAC Address:	<input type="text" value="xx-xx-xx-xx-xx-xx"/> <input type="button" value="Clone MAC Address"/>
<input type="button" value="Save"/>	

## Q3. How do I restore the router to its factory default settings?

- A1. While the Archer C20 is powered on, press and hold the WPS/Reset button on the rear panel of the router until all LEDs turn on momentarily.
- A2. Log in to the Web Management page of the router, and go to **System tools->Factory Defaults**, click **Restore**, then wait until the progress bar loading finishes.



## Q4. What can I do if I forget my password?

- **Web Management page password:**
  - A. Restore the router to its factory default settings and then use the default User Name 'admin' and Password 'admin' to log in.
- **Wireless Network password:**
  - A1. The factory default password can be found on the product label printed on the bottom of the router.
  - A2. If you have changed your password, log in to the router's Web Management page, go to **Wireless>Wireless Security** to obtain or reset your password.

Note: If your questions are not answered here, please refer to <http://www.tp-link.com/en/support/faq> and click **Contact Technical Support** for further assistance.

# LED Indicators

Name	Status	Indication
(Power)	Off Flashing On	Power is off. The router is starting or upgrading firmware. Power is on.
(Wireless 2.4G)	Off On	The wireless function is disabled. The wireless function is enabled. The router is working on 2.4GHz radio band.
(Wireless 5G)	Off On	The wireless function is disabled. The wireless function is enabled. The router is working on 5GHz radio band.
(Ethernet)	Off On	No device is connected to the Ethernet ports. At least one device has connected to the Ethernet ports.
(Internet)	Blue Orange Off	The Internet port is connected, and the Internet is accessible. The Internet port is connected, but the Internet is inaccessible. The Internet port is not connected, and the Internet is inaccessible.
(USB)	Off Flashing On	No USB device is plugged into the USB port. A plugged-in USB device is being recognized. The USB device has been successfully recognized.
(WPS)	Slow Flash On Quick Flash	A wireless device is connecting to the network by WPS function. This process will last in the first 2 minutes. A wireless device has been successfully added to the network by WPS function. A wireless device failed to be added to the network by WPS function.