



How to upgrade TP-LINK Wireless G Router&AP

Notice:


- **Please verify the hardware version of your device for the firmware version. Wrong firmware upgrading may damage your device and void the warranty.**



	Published Date	8/25/2010
	File Size	3.614 MB
	Operating System	Win98SE/Me/NT/2000/XP/2003/Vista/Windows 7/Linux
	Modifications and Bug Fixes	<ul style="list-style-type: none">• Fix some problems about IPsec.• Fix some bugs about PoE.• Fix display problem on wireless page.• Add support to No-IP DDNS.• Time can be set manually or sync with PC.
	Notes	

- After you downloaded the firmware from TP-LINK website, **please use decompression software such as WinZIP or WinRAR to extract the firmware file to a folder;**
- Do NOT upgrade the firmware via **wireless** connection;
- Do NOT turn off the power or cut down the Ethernet cable during upgrade process;
- **Please write down all current settings as a backup and enter them manually after upgrading.**
- Internet Explorer(IE) is recommended to upgrade the firmware.

Step 1 Log into the TP-LINK device by typing <http://192.168.1.1> in the address bar of the web browser (such as Internet Explorer, Firefox). The **User Name** and **Password** are both **admin** unless you have changed it before.



Step 2 Click **System Tools->Firmware**, click the **Browse** button to choose the firmware you already extracted in the folder.

Firmware

File:	<input type="text"/>	<input type="button" value="Browse..."/>
Firmware Version:	3.5.4 Build 070809 Rel.31767n	
Hardware Version:	WR543 v1 081520EF	

Step 3 Click the **Upgrade** button. The device will reboot automatically after the upgrading has been finished. Please wait about 3 minutes.

Step 4 Click **Status**, verify that the router's firmware has been upgraded.

Status

Firmware Version:	4.2.1 Build 090106 Rel.56881n
Hardware Version:	WR340G v2 08118989

Step 5 It is recommended that restoring the device to factory default to make the new functions take effect; Click **System Tools->Factory Defaults**, Click **Restore** Button.

Factory Defaults

Click the following button to reset all configuration settings to their default values.

Step 6 After restoring factory default, please login <http://192.168.1.1> and re-enter the settings you have written down before upgrading.