

How to upgrade TP-LINK Range Extender

Notice:


- **Please verify the hardware version of your device for the firmware version. Wrong firmware upgrading may damage your device and void the warranty.**



TL-WA730RE V2 130510	Published Date	2013/5/10
	Language	English
	File Size	3.46 MB
	Operating System	Win2000/XP/2003/Vista/7/8/Mac/Linux
	Modifications and Bug Fixes	1. Fixed an ARP broadcast storm problem caused by IP conflict; 2. Fixed a compatible problem in Thailand; 3. Fixed a bug that wireless may encounter disconnection when there are over 8 clients with powersave enabled; 4. Fixed some vulnerabilities and improved security.
	Notes	For TL-WA730RE V2

- **After you downloaded the firmware from TP-LINK website, please use decompression software such as WinZIP or WinRAR to extract the firmware file to a folder;**
- **Do NOT upgrade the firmware via wireless connection unless the device only has wireless connection;**
- **Do NOT turn off the power or cut down the Ethernet cable during upgrade process;**
- **Please write down all the settings which you changed from the default values, since you may need to reenter them manually.**

Step 1 Log into the TP-LINK device by typing <http://tplinkrepeater.net/> in the address bar of the web browser (such as Internet Explorer). The username and password are both **admin** unless you have changed it before.



Step 2 Click **System Tools -> Firmware Upgrade**, click the **Browse** button to choose the firmware you already extracted in the folder.

Firmware Upgrade

New Firmware File:

Browse

Firmware Version:

1.0.0 Build 20150611 Rel. 60542

Hardware Version:

RE450 v1.0

Upgrade

Step 3 Click the **Upgrade** button. The device will reboot automatically after the upgrading has been finished. Please wait about 3 minutes.

Status

Region

Wireless

Network

System Tools

- Time Settings
- LED Control
- Firmware Upgrade
- Backup & Restore
- Admin Account
- System Log

Internet Router Range Extender Clients

Range Extender

Extended 2.4GHz		Extended 5GHz	
SSID:	TP-LINK_Extender_2.4GHz	SSID:	TP-LINK_Extender_5GHz
Channel:	11	Channel:	36
MAC Address:	00-0A-EB-13-7B-00	MAC Address:	00-0A-EB-13-7B-02

Wired

DHCP Server:	Auto (Off)
IP Address:	192.168.0.100
Type:	Dynamic IP

Firmware Version: 1.0.0 Build 20150611 Rel. 60542 Hardware Version: RE450 v1.0 Support

Step 4 Click **Status**, verify that the device's firmware has been upgraded.

Step 5 Then, check the status page of your device, if necessary please re-enter or reconfigure the device manually with the parameters you have written down before upgrading.