


How to upgrade TP-LINK ADSL Modem Router

Notice:

- **Please verify the hardware version of your device for the firmware version. Wrong firmware upgrading may damage your device and void the warranty.**



 TD-W8960N V1 10082 5	Published Date	8/25/2010
	File Size	3.614 MB
	Operating System	Win98SE/Me/NT/2000/XP/2003/Vista/Windows 7/Linux
	Modifications and Bug Fixes	<ul style="list-style-type: none">• Fix some problems about IPSec.• Fix some bugs about IPoE.• Fix display problem on wireless page.• Add support to No-IP DDNS.• Time can be set manually or sync with PC.
	Notes	

- **After you downloaded the firmware from TP-LINK website, please use decompression software such as WinZIP or WinRAR to extract the firmware file to a folder;**
- **Do NOT upgrade the firmware via wireless connection;**
- **Do NOT turn off the power or cut down the Ethernet cable during upgrade process;**
- **Please write down all current settings as a backup and enter them manually after upgrading.**
- **Internet Explorer(IE) is recommended to upgrade the firmware.**

Step 1 Log into the ADSL Modem Router by typing <http://192.168.1.1> in the address bar of the web browser (such as Internet Explorer, Firefox). The User Name and Password are both **admin** unless you have changed it before.



Step 2 Click **System Tools -> Firmware Upgrade**, click the **Browse** button to choose the firmware you already extracted in the folder.


Operation Mode	<p>You'll get new functions after upgrading the firmware of the router.</p> <p>Firmware File Path: <input type="text"/> <input type="button" value="Browse..."/></p> <p>Firmware version: 0.6.0 1.1 v0005.0 Build 120926 Rel.27100n</p> <p>Hardware version: TD-W8968 v1 00000000</p> <p>Note:</p> <ol style="list-style-type: none"> 1. Please select the right firmware version corresponding to the hardware version of this device. 2. It is important to keep power on during the whole process to avoid damage to the device. 3. The upgrade process takes about 50 seconds, after that, the modem router will reboot automatically. <p><input type="button" value="Upgrade"/></p>
Network	
DHCP Server	
Wireless	
USB Settings	
Route Settings	
Forwarding	
Parent Control	
Firewall	
IPv6 Firewall	
IPv6 Tunnel	
Bandwidth Control	
IP & MAC Binding	
Dynamic DNS	
Diagnostics	
System Tools	
System Log	
Time Settings	
Manage Control	
CVMP Settings	
SNMP Settings	
Backup & Restore	
Factory Defaults	
Firmware Upgrade	
Reboot	

Step 3 Click the **Upgrade** button. The device will reboot automatically after the upgrading has been finished. Please wait about 3 minutes.

Step 4 Click **Status**, verify that the router's firmware has been upgraded.

Status	Basic Status
Quick Setup	
Operation Mode	
Network	
DHCP Server	
Wireless	
	<p>Device Information</p> <p>Firmware Version: 0.6.0 1.1 v0005.0 Build 120926 Rel.27100n</p> <p>Hardware Version: TD-W8968 v1 00000000</p> <p>System up time: 0 day(s) 00:16:11</p>

Step 5 It is recommended that restoring the device to factory default to make the new functions take effect; Click **System Tool->Factory Default**, Click **Restore** Button.



Step 6 After restoring factory default, please login <http://192.168.1.1> and re-enter the settings you have written down before upgrading.