

How to upgrade TP-LINK Wireless Access Point

Notice:

- Please verify the hardware version of your device for the firmware version. Wrong firmware upgrading may damage your device and void the warranty.



	Published Date	2013/8/28
	Language	English
	File Size	3.50 MB
	Operating System	Win2000/XP/2003/Vista/7/8/Mac/Linux
	Modifications and Bug Fixes	<ol style="list-style-type: none">1. Added gateway option under LAN section.2. Added "Allow remote access" option.3. Removed the function of logging the management page with any domain.
	Notes	For TL-WA901ND V3

- After you downloaded the firmware from TP-LINK website, please use decompression software such as WinZIP or WinRAR to extract the firmware file to a folder;
- It's recommended to upgrade the firmware via cable connection;
- Do NOT turn off the power or cut down the Ethernet cable during upgrade process;
- Because after upgrading the old settings may be lost, so please write down the key settings as a backup before you start to upgrade.

Step 1 Log into the TP-LINK device by typing <http://tplinkap.net/> in the address bar of the web browser (such as Internet Explorer, Firefox). The username and password are both **admin** unless you have changed it before.



Step 2 Click **System Tools ->Firmware Upgrade**, click the **Browse** button to choose the firmware you already extracted in the folder.

Firmware Upgrade

File: **Browse...**

Firmware Version: 3.12.11 Build 110915 Rel.40896n

Hardware Version: WR740N v4 00000000

Upgrade

Step 3 Click the **Upgrade** button. The device will reboot automatically after the upgrading has been finished. Please wait about 3 minutes.

Step 4 Click **Status**, verify that the device's firmware has been upgraded.

Status

Firmware Version: **3.12.11 Build 111130 Rel.55312n**

Hardware Version: WR740N v4 00000000

Step 5 Then, check the status page of your device, if necessary please re-enter or reconfigure the device manually with the parameters you have written down before upgrading.